



Oily dielectric deoxidizer (M201)

This spray is perfect to protect electric parts and electric contacts, and it's ideal for both professional and for do-it-yourself uses. It prevents oxidation, it removes residuals and impurity and it has a degrease power. Find out all the potential of this product!



HOW TO USE: shake the cylinder. Spray directly on surface to be treated from a distance of about 20 cm. Do not apply to equipment in tension. Do not apply to overheated materials. Apply power only after the complete evaporation of the product or dry it perfectly first.

Quantity	400 ml
Barcode	EAN 13: 8034108892399
Confection	12 pz

OILY DIELECTRIC DEOXIDIZER – Specific product that leaves an oily film to protect the electrical equipment and electrical contacts from oxidation. It prevents and eliminates the formation of residue and impurities that prevent the proper functioning of it. It has an excellent degreasing power, it promotes conductivity and it is water repellent. Do not use on live equipment.

Technical Specifications:

Aspect	Cylinder containing under pressure fluid
Color	Light brown
Odour	Characteristic of solvent
Relative density	at 20°C 0,71 ÷ 0,75 g/ml
Flash point	Low. 0° C
Pressure at 20°C	4/6 bar
Viscosity at 50°C	11 ÷ 24 cst (of the active ingredient)
Solubility	Insoluble in water
Auto-ignition temperature	> 400 ° C (of the active ingredient)
Corrosion on copper	(ASTM D 130): 1 (of the active ingredient)

MODALITY OF STORAGE

Before using: stock the product in a dry location and don't stock it with a temperature under 0° degrees and over 45°C, after the use, keep containers closed. In the original package, the product can be conserved for 24 months.

After the first usage: conserve in a fresh and dry location, away from hot spring. Keep out of reach of children.

Hazards identification:

H222	Extremely flammable aerosol.
H229	Pressurized container: it may burst if heated.
H319	Causes serious eye irritation.
H336	Causes skin irritation.
EUH066	Repeated exposure may cause skin dryness or cracking.

This information, even if reliable, must be considered only approximate. The usage don't imply our responsibility, included the violation of many license. Before using, the users have to verify the suitability of the product for the specific use.